



(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication:  
27.12.2000 Bulletin 2000/52

(51) Int Cl. 7: **H04B 7/04**

(21) Application number: 99112131.0

(22) Date of filing: 23.06.1999

(84) Designated Contracting States:  
**AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU  
MC NL PT SE**  
Designated Extension States:  
**AL LT LV MK RO SI**

- Enderlein, Janos, c/o Sony Int.(Europe) GmbH  
70736 Fellbach (DE).
- Zumkeller, Markus, c/o Sony Int.(Europe) GmbH  
70736 Fellbach (DE)

(71) Applicant: Sony International (Europe) GmbH  
10785 Berlin (DE)

(74) Representative:  
**MÜLLER & HOFFMANN Patentanwälte**  
Innere Wiener Strasse 17  
81667 München (DE)

(72) Inventors:  
• Kraiem, Besma, c/o Sony Int.(Europe) GmbH  
70736 Fellbach (DE)

(54) **Transmit and receiving antenna diversity**

(57) Performing an antenna diversity set-up according to the present invention a first mobile terminal (1) transmits a pre-defined antenna calibration signal to a second mobile terminal (15) using its omni-directional antenna (10). During the period of the transmitted signal the best receiving antenna (x) is identified at the second mobile terminal (15) by switching all its directional antennas (21 to 28) and its omni-directional antenna (20) into its receiving path and measuring the received signal quality, e. g. the received signal strength. The directional antenna (x) of the second network device (15) which is identified as best receiving antenna is then used for

transmission and reception of data transfer with the first network device (1). Using this antenna, the second network device (15) transmits its pre-defined calibration signal to the first network device (1) which repeats a similar switching and measuring procedure with its directional antennas (11 to 14) and its omni-directional antenna (10) to identify its best receiving antenna (y). These two antennas (x, y) identified at the second network device (15) and the first network device (1) are then used for direct data transfer in-between these both devices. This inventive method is preferably used in direct mode within an IEEE1394 based HIPERLAN type 2 wireless network.




Fig. 1

## Description

[0001] The present invention relates to transmit and receiving antenna diversity in wireless networks, in particular in wireless networks with direct mode, i. e. the possibility that network devices, e. g. mobile terminals, directly communicate with each other without using a central station or access point as repeater.

[0002] An exemplary wireless network is shown in Fig. 3. Generally, mobile terminals in wireless networks, such as the IEEE 1394 based HIPERLAN type 2 network which is developed under supervision of ETSI comprise several different directed antennas to be able to perform a receiving antenna diversity in regard to the central controller or access point 18. In this case the receiver of a mobile terminal 1, 15, 16, 17 determines the best receiving antenna during a downlink period of a communication with the central controller or access point 18 and the transmitter of said mobile terminal uses the same antenna during an uplink period. An IEEE 1394 bus with connected network devices is exemplary shown only for the fourth mobile terminal 17.

[0003] The state of the art on both transmit and receiving antenna diversity in wireless networks with direct mode is performed by switching between all transmit and receiving antennas in order to assess the provided radio link quality in all possible cases. In case a first mobile terminal having a medium access control identifier, i. e. MAC-ID, MT1 comprises N directed transmit and receiving antennas and a second mobile terminal having medium access control identifier MT2 comprises M directed transmit and receiving antennas there is the need to perform N M measurements until the best antenna pair is identified, since for each of the N directed transmit antennas of the first mobile terminal with MAC-ID MT1 all M receiving antennas of the second mobile terminal with MAC-ID MT2 have to be switched through to determine the antenna pair having the best performance. These N M measurements need a rather long time when considering systems with a bigger number of transmitting and receiving antennas, e. g. 8 antennas per mobile terminal.

[0004] Therefore, it is the object of the present invention to reduce the time to identify the best antenna pair in case of transmit and receiving antenna diversity.

[0005] This object is solved with a method to perform a transmit and receiving antenna diversity in-between a first network device and a second network device of a wireless network according to independent claim 1, a network device within a wireless network which is comprising a number of directional antennas according to independent claim 4 and an antenna calibration signal according to independent claim 11. Preferred embodiments thereof are respectively defined in the dependent subclaims.

[0006] According to the present invention a network device of a wireless network, such as a mobile terminal of an IEEE 1394 based HIPERLAN type 2 network, which comprises a number of directional antennas to perform antenna diversity additionally comprises an omni-directional antenna.

[0007] Therewith, to perform a transmit and receiving antenna diversity in-between first and second of such network devices according to the present invention the following steps are performed:

- using the omni-directional antenna of the first network device to transmit a calibration signal from the first network device to the second network device;
- identifying the best receiving antenna of the second network device by successively switching all directional antennas and the omni-directional antenna of the second network device into its receiving path and respectively measuring the received signal quality, and setting said identified best receiving antenna as transmit and receiving antenna of said second network device;
- using the set transmit and receiving antenna of said second network device to transmit a calibration signal from the second network device to the first network device; and
- identifying the best receiving antenna of the first network device by successively switching all directional antennas and the omni-directional antenna of the first network device into its receiving path and respectively measuring the received signal quality, and setting said identified best receiving antenna as transmit and receiving antenna of said first network device.

[0008] Therewith, according to the present invention the amount of measurements needed to be performed until the best antenna pair is identified is reduced to  $N + M + 2$  in case the first network device comprises N directional antennas and 1 omni-directional antenna and the second network device comprises M directional antennas and 1 omni-directional antenna.

[0009] Said omni-directional antenna of a network device according to the present invention is preferably separate from the directional antennas, but according to a further preferred embodiment of the present invention it is also possible that said omni-directional antenna is build by a parallel connection of several or all of said directional antennas.

[0010] This further preferred embodiment according to the present invention has the advantage that existing network devices can easily be adapted to the inventive method without considerable changes in hardware, but by mainly providing the new control method for antenna diversity according to the present invention.

[0011] An antenna calibration signal that is to be used in the inventive method to perform a transmit and receiving

antenna diversity with a network device according to the present invention is characterized in that a signal is used which is already available within the mobile terminal.

[0012] Therefore, no additional memory space is needed to store the calibration signal according to the present invention.

[0013] Preferably one or more B16 quarter symbols are used to compose the antenna calibration signal, wherein a B16 is a quarter symbol within a BCCH/uplink preamble according to the IEEE 1394 based HIPERLAN type 2 network.

[0014] To use of this signal inherits the advantage that the peak to average power ratio and dynamic range is low.

[0015] Of course, the calibration signal has to be transmitted during the whole time of switching through all available antennas of the respective receiving network device and it has to be homogeneous over its signal period.

[0016] The present invention and its numerous embodiments will be better understood from the following detailed description of an exemplary preferred embodiment thereof taken in conjunction with the accompanying drawings, in which

**Fig. 1** shows two mobile terminals of an IEEE 1394 HIPERLAN type 2 network adapted according to the present invention;

**Fig. 2** shows the antenna diversity set-up in direct mode for both mobile terminals shown in Fig. 1; and

**Fig. 3** shows an exemplary IEEE 1394 based HIPERLAN type 2 network.

[0017] Fig. 1 shows that the first mobile terminal 1 having the medium access control identifier, i. e. MAC-ID, MT1 has  $N = 4$  directional antennas 11 to 14 and one omni-directional antenna 10 which are connected via a switching unit 9 to the movable terminal of a transmit/receive selection switch 2 which fixed terminals are respectively connected to the transmitter and receiver signal path of the mobile terminal 1. In the receiver signal path a receiver 3 is directly connected to the respective fixed terminal of the transmit/receive selection switch 2. This receiver 3 produces a data and control signal input to a controller 6 and also outputs a signal wherefrom a signal quality measurement unit 5 can determine the received signal strength which is output to the controller 6. For the transmitter signal path the controller 6 outputs a data and control signal to a transmitter 4 which modulates, up-converts and amplifies this signal to a given signal strength which is indicated to the transmitter 4 by a control signal generated by the controller 6 and outputs the generated transmission signal to the respective fixed terminal of the transmit/receive selection switch 2. Bi-directionally connected to the controller are a user interface 7 and a memory 8. Furtheron, the controller 6 outputs a antenna selection signal to the switching unit 9.

[0018] The second mobile terminal 15 having a medium access control identifier MT2 looks identical to the first mobile terminal 1 apart from the fact that it comprises  $M = 8$  directional antennas 21 to 28 and one omni-directional antenna 20 which are respectively connected to the switching unit 9.

[0019] In the following the antenna diversity set-up in direct mode between the first mobile terminal 1 having the medium access control identifier MT1 and the second mobile terminal 15 having the medium access control identifier MT2 is explained in connection with Fig. 2.

[0020] For example, after the direct mode connection set-up and a transmit power control the access point/central controller 18 grants resources for the peer mobile terminals, i. e. the first mobile terminal 1 and the second mobile terminal 15, to perform antenna diversity selection. Therefore, using its omni-directional antenna 10, the first mobile terminal 1 with MAC-ID MT1 transmits an antenna diversity calibration signal, in the following AD\_signal, to the second mobile terminal 15 with MAC-ID MT2 in a first step S1.

[0021] During the period of the transmitted signal the best receiving antenna is identified at the second mobile terminal 15 with MAC-ID MT2, by switching the  $M = 8$  directional antennas 21 to 28 and the omni-directional antenna 20 into the receiving path and then measuring the received signal quality, e. g. the received signal strength RSS. The directional antenna x at the second mobile terminal 15 with MAC-ID MT2 which is identified as best receiving antenna, e. g. the first directional antenna 21 of the second mobile terminal 15, is then used for transmission and reception of direct mode transfer with the first mobile terminal 1 with MAC-ID MT1. Using this antenna the second mobile terminal 15 transmits its AD\_signal to the first mobile terminal 1 in a second step S2.

[0022] The first mobile terminal 1 performs a similar switching and measuring procedure with its  $M = 4$  directional antennas 11 to 15 and its omni-directional antenna 10 to identify its best receiving antenna y, e. g. the second antenna 12 of the first mobile terminal 1. These two antennas y and x identified at the first mobile terminal 1 and the second mobile terminal 15 are then used for data transfer in direct mode in-between these both mobile terminals.

[0023] Basically, the numbers N and M of directional antennas depend on the system used, preferably  $N = M \leq 8$  directional antennas are used.

[0024] In the following the requirements of the antenna calibration signal are listed and explained:

- the length of the signal has to be sufficient for switching and measuring the maximum number of antennas used within a mobile terminal,

## EP 1 063 789 A1

- the strength of the signal has to be homogenous over its signal period,
- the peak to average power ratio and dynamic range has to be low, and
- in order to avoid additional space for the signal storage a signal shall be applied which is already available.

[0025] Of course, depending on the needs of the system not all of these 4 items have to be fulfilled simultaneously.

[0026] As mentioned above, the best antenna arrangement will be found by subsequently switching of all antennas into the receiving path and measuring of the signal strength. Table 1 below contains an estimation of the time (specified in parts of a symbol length for the IEEE 1394 based HIPERLAN type 2 network) needed for measurement of the signal and switching from one antenna to the next.

Table 1:

Length of the antenna calibration signal for one antenna	
Function	Symbol
Signal collection and energy integration over antenna n	3/4
Setting-up a switching to antenna n + 1	1/4

[0027] As shown in Table 1, for the measurement and switching of one antenna a time of approximately one OFDM symbol, i. e. 3,2  $\mu$ s, is needed, wherefore for N = 8 directional antennas and one omni-directional antenna a calibration signal with a length of 9 symbols = 28,8  $\mu$ s is necessary.

[0028] Preferably each of these 9 OFDM symbols is composed by 4 quarter symbols as they have been introduced for the BCCH/uplink preamble within the IEEE 1394 based HIPERLAN type 2 standard. As required, the time domain waveform of the B16 symbols achieves a low peak to average power ratio and a small dynamic range. Therefore, it is preferred to use B16 symbols to compose the antenna calibration signal.

[0029] Of course, the present invention is not limited to IEEE 1394 and also not to HIPERLAN type 2. In general, any wireless network and network devices within such a network supporting antenna diversity are applicable to the present invention. Also, the present invention is not limited to direct mode only, it is also thinkable that antenna diversity according to the present invention can be performed in-between a mobile terminal and the central controller/access point.

### Claims

1. Method to perform a transmit and receiving antenna diversity in-between a first network device (1) and a second network device (2) of a wireless network, **characterized by the following steps:**

- using an omni-directional antenna (10) of the first network device (1) to transmit a calibration signal from the first network device (1) to the second network device (15);
- identifying the best receiving antenna (x) of the second network device (15) by successively switching all directional antennas (21 to 28) and an omni-directional antenna (20) of the second network device (15) into its receiving path and respectively measuring the received signal quality, and setting said identified best receiving antenna (x) as transmit and receiving antenna of said second network device (15);
- using the set transmit and receiving antenna (x) of said second network device (15) to transmit a calibration signal from the second network device (15) to the first network device (1); and
- identifying the best receiving antenna (y) of the first network device (1) by successively switching all directional antennas (11 to 14) and said omni-directional antenna (10) of the first network device (1) into its receiving path and respectively measuring the received signal quality, and setting said identified best receiving antenna (y) as transmit and receiving antenna of said first network device (1).

2. Method according to claim 1, **characterized in that** said wireless network is an IEEE 1394 based HIPERLAN type 2 network.

3. Method according to claim 1 or 2, **characterized in that** said network device is a mobile terminal (1, 15) or a central controller (18).

4. Network device (1; 15) within a wireless network, comprising a number of directional antennas (11 to 14; 21 to 28), **characterized by** an omni-directional antenna (10; 20).

EP 1 063 789 A1

5. Network device according to claim 4, **characterized in that** said omni-directional antenna (10; 20) is build by a parallel connection of at least one of said directional antennas (11 to 14; 21 to 28).
6. Network device according to claim 5, **characterized in that** said omni-directional antenna (10; 20) is build by a parallel connection of all of said directional antennas (11 to 14; 21 to 28).
7. Network device according to any one of claims 4 to 6, **characterized by** a maximum of 8 directional antennas.
8. Network device according to any one of claims 4 to 7, **characterized in that** it is a mobile terminal or a central controller.
9. Network device according to any one of claims 4 to 8, **characterized in that** it is used in an IEEE 1394 based HIPERLAN type 2 wireless network.
10. Network device according to any one of claims 4 to 9, **characterized in that** it is adapted to perform the method to perform a transmit and receiving antenna diversity according to claim 1, 2 or 3.
11. Antenna calibration signal to be used in a method to perform a transmit and receiving antenna diversity according to claim 1, 2 or 3 with a mobile terminal according to any one of claims 4 to 10, **characterized in that** it is a signal which is already available within the network device.
12. Antenna calibration signal according to claim 11, **characterized in that** it consists of one or more B16 quarter symbols which respectively are used as BCCH/uplink preamble in a HIPERLAN type 2 network.




Fig. 1




Fig. 2




Fig. 3

EP 1 063 789 A1



European Patent  
Office

# EUROPEAN SEARCH REPORT

Application Number  
EP 99 11 2131

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
X	US 4 369 520 A (CERNY JR FRANK J ET AL) 18 January 1983 (1983-01-18) * abstract; figure 1 *	4-9	H04B7/04
X	US 5 828 658 A (OTTERSTEN BJOERN E ET AL) 27 October 1998 (1998-10-27) * figures 1,2 * * column 15, line 29 - line 36 * * column 18, line 36 - line 39 * * column 27, line 45 - line 52 *	4,7-9	
A	EP 0 622 911 A (IBM) 2 November 1994 (1994-11-02) * abstract; figures 4,6 * * column 2, line 26 - column 3, line 11 * * column 4, line 33 - column 6, line 47 *	1,3,10,11	
A	GB 2 298 338 A (MOTOROLA LTD) 28 August 1996 (1996-08-28) * abstract; figure 5 * * page 9, line 1 - page 10, line 2 *	1,3,10,11	
A	WEI-LIN LIU ET AL: "Advanced low-complexity HIPERLAN receiver using combined antenna switching diversity and simple equaliser" 1997 IEEE 47TH. VEHICULAR TECHNOLOGY CONFERENCE, PHOENIX, MAY 4 - 7, 1997, vol. 3, no. CONF. 47, 1997, pages 2037-2041 2041 vol.3, XP002101330 INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS ISBN: 0-7803-3660-7 * abstract; figure 7 *	1-4,8,9,11,12	H04B
The present search report has been drawn up for all claims			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
Place of search THE HAGUE		Date of completion of the search 4 November 1999	Examiner Sieben, S
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

CPO FORM 1503 03/02 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT  
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 11 2131

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on  
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

04-11-1999

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
US 4369520	A	18-01-1983	CA	1141825 A	22-02-1983
US 5828658	A	27-10-1998	US	5592490 A	07-01-1997
			US	5515378 A	07-05-1996
			US	5546090 A	13-08-1996
			AU	5086498 A	15-05-1998
			EP	0932986 A	04-08-1999
			WO	9818272 A	30-04-1998
			US	5886988 A	23-03-1999
			AU	701764 B	04-02-1999
			AU	4595296 A	07-08-1996
			BR	9510197 A	23-12-1997
			CA	2210859 A	25-07-1996
			CN	1173265 A	11-02-1998
			EP	0804858 A	05-11-1997
			FI	973076 A	16-09-1997
			JP	11504169 T	06-04-1999
			WO	9622662 A	25-07-1996
			AT	183865 T	15-09-1999
			AU	670766 B	01-08-1996
			AU	3145493 A	19-07-1993
			CA	2125571 A	24-06-1993
			DE	69229876 D	30-09-1999
			EP	0616742 A	28-09-1994
			EP	0926916 A	30-06-1999
			FI	942771 A	10-06-1994
			JP	7505017 T	01-06-1995
			WO	9312590 A	24-06-1996
			US	5625880 A	29-04-1997
			US	5642353 A	24-06-1997
EP 0622911	A	02-11-1994	US	5507035 A	09-04-1996
			BR	9401624 A	22-11-1994
			CA	2113734 A	31-10-1994
			CN	1096616 A	21-12-1994
			JP	2692779 B	17-12-1997
			JP	6334636 A	02-12-1994
			KR	9707606 B	13-05-1997
GB 2298338	A	28-08-1996	NONE		